


## HOA7720/7730 Series

### Connectorized Transmissive Optoschmitt Sensor



#### DESCRIPTION

The HOA7720/7730 Series consists of an infrared emitting diode facing an Optoschmitt detector encased in a black thermoplastic housing. The photodetector consists of a photodiode, amplifier, voltage regulator and Schmitt trigger with either of two output configurations:

- Totem pole (HOA7720-M11)
- Open collector (HOA7730-M11)

The totem pole output is well-suited for applications which require fast transition times. The open collector allows the output of the sensor to interface with circuit elements driven by supply voltages other than Vcc supply.

The inverting logic provides a high output when the optical path is interrupted, and a low output when the path is clear.

#### FEATURES AND BENEFITS

- Direct TTL interface
- No interface circuits required
- Inverting logic
- Two output options
- High resolution
- 3.00 mm [0.118] slot width
- Integral 3-pin connector

The infrared emitting diode is biased internally, eliminating the need for any external circuitry. Interconnection is simplified through the use of the integral Tyco three-pin connector.

Both the emitter and detector have a 0.508 mm x 1,78 mm [0.020 in x 0,070 in] vertical aperture. The narrow aperture is ideal for use in applications in which the maximum rejection of ambient light is important, and the maximum position resolution is desired.

The HOA7720/7730 series employ plastic molded components. Housing material is opaque polycarbonate. Housings are soluble in chlorinated hydrocarbons and ketones. Recommended cleaning agents are methanol and isopropanol.

#### POTENTIAL APPLICATIONS

##### Industrial:

- Flag presence/absence detection
- Edge detection
- Rotary/linear encoders

##### Medical:

- Edge sensing for labels and paper
- Needle presence/absence detection
- End of motion/travel sensing
- Rotary/linear encoders



# HOA7720/7730 Series

**Table 1. HOA7720-M11 and HOA7730-M11 Absolute Maximum Ratings (At 25 °C [77 °F] free air temperature unless otherwise noted.)**

Characteristic	Parameter
Operating temperature range	-40 °C to 70 °C [-40 °F to 158 °F]
Storage temperature range	-40 °C to 85 °C [-40 °F to 185 °F]
Power dissipation	220 mW
Supply voltage	5.5 V
Supply current	40 mA
Low level output current	12.8 mA
Duration of output: short to Vcc or ground	1.0 s
Applied output voltage <sup>1</sup>	35 V

**Notes:**

1. Applies to HOA7730 only.

**Table 2. HOA7720-M11 Electrical Characteristics (At 25 °C [77 °F] unless otherwise noted.)**

Characteristic	Symbol	Min	Typ.	Max	Unit	Test Condition
Operating supply voltage <sup>1</sup>	V <sub>CC</sub>	4.5	–	5.5	V	T <sub>A</sub> = 25 °C
Supply current	I <sub>CC</sub>	–	–	40	mA	V <sub>CC</sub> = 5.5 V
Low level output voltage <sup>2</sup>	V <sub>OL</sub>	–	–	0.4	V	V <sub>CC</sub> = 4.5 V, I <sub>OL</sub> = 12.8 mA
High level output current <sup>2</sup>	V <sub>OH</sub>	2.4	–	–	V	V <sub>CC</sub> = 4.5 V, I <sub>OH</sub> = -800 µA
Short circuit output current	I <sub>OS</sub>	-20	–	-100	mA	V <sub>CC</sub> = 5.25 V, Output = GND
Hysteresis <sup>3</sup>	HYST	–	50	–	%	–
Propagation delay, low-high, high-low	t <sub>PLH</sub> , t <sub>PHL</sub>	–	5	–	µs	V <sub>CC</sub> = 5 V
Output rise time, output fall time	t <sub>r</sub> , t <sub>f</sub>	–	70	–	ns	RL = 8 TTL loads

**Notes:**

1. Add a bypass capacitor, 0.1 µF typ., between Vcc and GND near the device in order to stabilize power supply line.
2. Output is HI when the optical path is interrupted.
3. Hysteresis is defined as the difference between the operating and release threshold intensities and is expressed as a percentage of the operate threshold intensity.

**Table 3. HOA7730-M11 Electrical Characteristics (At 25 °C [77 °F] unless otherwise noted.)**

Characteristic	Symbol	Min	Typ.	Max	Unit	Test Condition
Operating supply voltage <sup>1</sup>	V <sub>CC</sub>	4.5	–	5.5	V	T <sub>A</sub> = 25 °C
Supply current	I <sub>CC</sub>	–	–	40	mA	V <sub>CC</sub> = 5.5 V
Low level output voltage <sup>2</sup>	V <sub>OL</sub>	–	–	0.4	V	V <sub>CC</sub> = 4.5 V, I <sub>OL</sub> = 12.8 mA
High level output current <sup>2</sup>	I <sub>OH</sub>	–	–	100	µA	V <sub>CC</sub> = 4.5 V, V <sub>OH</sub> = 28 V
Hysteresis <sup>3</sup>	HYST	–	50	–	%	–
Propagation delay, low-high, high-low	t <sub>PLH</sub> , t <sub>PHL</sub>	–	5	–	µs	V <sub>CC</sub> = 5 V
Output rise time, output fall time	t <sub>r</sub> , t <sub>f</sub>	–	70	–	ns	RL = 390 Ω

**Notes:**

1. Add a bypass capacitor, 0.1 µF typ., between Vcc and GND near the device in order to stabilize power supply line.
2. Output is HI when the optical path is interrupted.
3. Hysteresis is defined as the difference between the operating and release threshold intensities. Expressed as a percentage of the operate threshold intensity.

# Connectorized Transmissive Optoschmitt Sensor

## Performance Graphics (typical values)

Figure 1. Inverter, Totem Pole




Figure 2. Inverter, Open Collector




Figure 3. Output Rise Time and Output Fall Time vs Temperature




Figure 4. Delay Time vs Temperature






Figure 5. Switching Waveform for Inverters



**Figure 6. Mounting Dimensions (For reference only: mm (in).)**



## Order Guide

Catalog Listing	Description
HOA7720-M11	Transmissive Optoschmitt sensor, totem pole output
HOA7730-M11	Transmissive Optoschmitt sensor, open collector output

## ⚠ WARNING

### PERSONAL INJURY

DO NOT USE these products as safety or emergency stop devices or in any other application where failure of the product could result in personal injury. Failure to comply with these instructions could result in death or serious injury.

## ⚠ WARNING

### MISUSE OF DOCUMENTATION

- The information presented in this product sheet is for reference only. Do not use this document as a product installation guide.
- Complete installation, operation, and maintenance information is provided in the instructions supplied with each product.

Failure to comply with these instructions could result in

**ywell**



Elblinger Elektronik GmbH  
Lange Wanne 25  
38259 Salzgitter

Telefon 05341/8212-1  
Fax 05341/821299

e-mail mail@elblinger-elektronik.de  
Internet www.elblinger-elektronik.de